

TELEVISION RECEIVER SPECIFICATIONS

1950-51

1950-51

Sales Features and Latest Prices of More Than 700 TV Models

MANUFACTURER	Model	Type	Picture Tube	List Price (Dollars)	Built-in Aerial	Set Also Receives	Record Player	Cabinet Finish	Mfr's. Chassis No.	Total Tubes**	Total Rectifiers	IF Frequency	Audio Output (watts)	Speaker Size & Type	
Admiral Corp., 3800 Cortland St., Chicago, Ill.	12 x 11	TA	12LP4	169.95	N	PL, EB	20Z1	17	2	25.75 I	...	PM 5	
	12 x 12	TA	12LP4	179.95	N	PL, MA	20Z1	17	2	25.75 I	...	PM 5	
	16 R 12	TA	16RP4	229.95	N	PL, MA	21B1	19	2	25.75 I	...	PM 8	
	26 R 12	C	16RP4	249.95	N	PL, MA	21B1	19	2	25.75 I	...	PM 8	
	26 x 55	C	16GP4	299.95	N	WA	24D1	21	3	25.75 S	...	PM 10	
	26 x 56	C	16GP4	309.95	N	MA	24D1	21	3	25.75 S	...	PM 10	
	26 x 57	C	16GP4	319.95	N	BL	24D1	21	3	25.75 S	...	PM 10	
	26 x 65	C	16GP4	329.95	N	WA	24D1	21	3	25.75 S	...	PM 10	
	26 x 66	C	16GP4	349.95	N	MA	24D1	21	3	25.75 S	...	PM 10	
	26 x 67	C	16GP4	369.95	N	BL	24D1	21	3	25.75 S	...	PM 10	
	26 x 75	C	16GP4	349.95	N	WA	24D1	21	3	25.75 S	...	PM 10	
	26 x 76	C	16GP4	369.95	N	MA	24D1	21	3	25.75 S	...	PM 10	
	29 x 25	C	19AP4	429.50	N	WA	24F1	21	3	25.75 S	...	PM 12	
	29 x 26	C	19AP4	449.50	N	MA	24F1	21	3	25.75 S	...	PM 12	
	29 x 17	C	19AP4	475.00	N	BL	24F1	21	3	25.75 S	...	PM 12	
	34 R 15	C	14CP4	329.95	N	AM	RC3	WA	20V1	21	2	25.75 I	...	PM 10	
	34 R 16	C	14CP4	349.95	N	AM	RC3	MA	20V1	21	2	25.75 I	...	PM 10	
	36 R 45	C	16RP4	399.95	N	AM-FM	RC3	WA	21C1	24	2	25.75 I	...	PM 12	
	36 R 46	C	16RP4	419.95	N	AM-FM	RC3	MA	21C1	24	2	25.75 I	...	PM 12	
	36 R 37	C	19AP4	465.00	N	AM-FM	RC3	BL	21C1	24	2	25.75 I	...	PM 12	
	39 x 35	C	19AP4	549.50	N	AM	RC3	WA	21J1	22	2	25.75 I	...	PM 12	
	39 x 36	C	19AP4	569.50	N	AM	RC3	MA	21J1	22	2	25.75 I	...	PM 12	
	39 x 25	C	19AP4	645.00	N	AM-FM	RC3	WA	24G1	26	3	25.75 S	...	PM 12	
	39 x 26	C	19AP4	665.00	N	AM-FM	RC3	MA	24G1	26	3	25.75 S	...	PM 12	
	39 x 17	C	19AP4	725.00	N	AM-FM	RC3	BL	24G1	26	3	25.75 S	...	PM 12	
	Air King Products Co., Inc. 170-53rd St., Brooklyn 32, N. Y.	12T2	TA	12LP4	169.95	N	WA	700	17	2	25.75 I	4	PM 5
		12T1	TA	12LP4	179.95	N	MA	700	17	2	25.75 I	4	PM 5
		12C1	CT	12LP4	199.95	N	MA	700	17	2	25.75 I	4	PM 5
		14T1	TA	14RP4	199.95	N	MA	700-3	17	2	25.75 I	4	PM 5
		16M1	TA	16RP4	219.95	N	MA, M	700-1	17	2	25.75 I	4	PM 5
16T1		TA	16RP4	249.95	N	MA	700-1	17	2	25.75 I	4	PM 5	
16C1		CT	16RP4	299.95	N	MA	700-1	17	2	25.75 I	4	PM 5	
718		C	16RP4	349.95	N	MA	700-1	17	2	25.75 I	4	PM 10	
19C1		C	19RP4	379.95	N	MA	700-40	17	2	25.75 I	4	PM 10	
18K1		C	16RP4	429.95	N	AM-FM	RC3	MA	700-S, 703	17	2	25.75 I	4	PM 8	
Andrea Radio Corp., 27-01 Bridge Plaza North, Long Island City, N. Y.	SAYBROOKE	TA	12DP4A	249.95	N	FM	MA, BL	VL12	21	2	26.2 S	3.5	PM 5	
	MAYFIELD	TA	16DP4	329.95	N	FM	MA, BL	VL15	21	4	26.2 S	3.5	PM 8	
	SUTTON	C	16GP4	439.50	N	MA, BL	VL16	21	4	26.2 S	3.5	PM 12	
	FLEETWOOD	C	16GP4	529.50	N	FM	RC3	MA, BL	VL16	21	4	26.2 S	3.5	PM 10	
	CARONIA 19	C	19AP4A	795.00	N	AM-FM	RC3	MA, BL	VL19	24	4	26.2 S	3	PM 12	
	NORMANDY	C	19AP4A	595.00	N	AM-FM	MA, BL	VK19	26	5	26.2 S	4	EM 12	
Ansley Radio & Television, Inc. 41 St. Joe's Ave., Trenton 9 N. J.	729	CT	16"	445.00	N	MA	703	24	5	25.75 S	3	PM 12	
	720	C	16HP4	795.60	N	AM-FM	RC3	MA	702	24	4	25.75 S	8	PM 12	
	723	TA	16"	295.00	N	MA	703	24	5	25.75 S	3	PM 12	
	724	C	16"	495.00	N	MA	703	24	5	25.75 S	8	PM 12	
	726	C	19"	565.00	N	MA	703	24	5	25.75 S	8	PM 12	
	730	C	21" Rect.	795.00	N	AM, FM	RC3	MA	39	4	25.75 S	8	PM 12	
	706	C	18"	1095.00	N	AM, FM	RC3	MA	39	4	25.75 S	8	PM 12	
	727	C	19"	1195.00	N	AM, FM	RC3	MA	39	4	25.75 S	8	PM 12	
Arvin Industries, Inc., Columbus, Ind.	2121TM	TA	12LP4A	169.95	N	PC	MA	TE-289	17	2	45.75 I	1.7	PM 5.5	
	2123TM	TA	12LP4A	149.95	N	PC	MA	TE-289	17	2	45.75 I	1.7	PM 5.5	
	2120CM	CT	12LP4A	199.95	N	PC	MA	TE-289	17	2	45.75 I	1.7	PM 5.5	
	2128CM	CT	12LP4A	179.95	N	PC	MA	TE-289	17	2	45.75 I	1.7	PM 5.5	
	2134CM	C	12LP4A	279.95	N	AM, FM	RC3	MA	TE-289	17	2	45.75 I	1.7	PM 5.5	
	4080T	TA	8AP4A	119.95	N	MA, BL	TE-282	16	2	45.75 I	1.0	PM 4	
	2161TM	TA	16KP4A	219.95	N	PC	MA	TE-290	18	2	45.75 I	2.0	PM 5.5	
	2160CM	CT	16KP4A	249.95	N	PC	MA	TE-290	18	2	45.75 I	2.0	PM 8	
	2164CM	CT	16KP4A	279.95	N	PC	MA	TE-290	18	2	45.75 I	2.0	PM 8	
	2162CCM	C	16KP4A	349.95	N	AM	RC3	MA	TE-290	18	2	45.75 I	2.0	PM 8x9	
	4162CM	CT	16KP4A	329.95	N	PC	MA	TE-288	24	2	45.75 I	3.0	PM 10	
	4162CB	CT	16KP4A	339.95	N	PC	BL	TE-288	24	2	45.75 I	3.0	PM 10	
Atwater Television Co., 360 Farman St., Brooklyn, N. Y.	X750	TA	16" Rect.	199.95	MA	18	2	I	...	PM 8	
	X800	CT	16" Rect.	249.95	MA	18	2	I	...	PM 8	
	X850	CT	19"	299.95	MA	18	2	I	...	PM 8	
	X351	TA	12 1/2"	149.95	MA	18	2	I	...	PM 4x8	
	X1400	TA	14" Rect.	159.95	MA	18	2	I	...	PM 5	
	X729	CT	16"	229.95	T	MA, BL	18	2	I	...	PM 10	
	513	C	18"	299.95	T	FM	MA, BL	21	3	S	...	PM 10	
	135	C	19"	389.95	T	FM	MA, BL	21	3	S	...	PM 10	
	X1800	C	16"	359.95	T	AM	RC3	MA, BL	21	3	S	...	PM 10	
	X1009	C	16"	279.95	T	MA, BL	21	3	S	...	PM 10	
Automatic Radio Mfg. Co., 122 Brookline Ave., Boston, Mass.	TV-5061	C	16DP4	299.95	MA	TV5061	19	..	25.75 I	2	PM 10	
	TV-5019	C	19DP4A	495.95	MA	TV5019	22	..	25.75 I	3	PM 10	
	TV-5118R	C	16TP4	299.95	MA	TV5118R	21	..	25.75 I	2	PM 10	
Bell Television, Inc., 552 W. 53rd St., New York 19, N. Y.	1603	CO	16AP4	295.00	MA	27	4	25.75 S	6	PM 12	
	1601	CO	19AP4A	445.00	MA	27	4	25.75 S	6	PM 12	
	1604	CO	16AP4	445.00	M	27	4	25.75 S	6	PM 12	
	1902	CO	19AP4	595.00	M, MA	27	4	25.75 S	6	PM 12	
	16T3	TA	16AP4	259.95	MA, WA	27	4	25.75 S	6	PM 12	
	16C3	CT	16AP4	299.95	MA, WA	27	4	25.75 S	6	PM 12	
	16D3	CT	16AP4	349.95	MA, WA	27	4	25.75 S	6	PM 12	
	19T4	TA	19AP4	359.95	MA, WA	27	4	25.75 S	6	PM 12	
	19C4	CT	19AP4	399.95	MA, WA	27	4	25.75 S	6	PM 12	
	19D4	CT	19AP4	449.95	MA, WA	27	4	25.75 S	6	PM 12	

(Continued on next page)

BL — Blond
C — Console
CH — Chassis
CO — Commercial
CT — Consolette
CU — Custom
EB — Ebony
EM — Electromagnetic
I — Inter-carrier
K — Kit
L — Leatherette
LO — Lined Oak
M — Metal
MA — Mahogany
MP — Maple
N — Non-tunable built-in ant.
O — Oak
PC — Phono Jack
PL — Plastic
PM — Permanent Magnet
RC3 — 3-speed record changer
S — Split sound IF system
SW — Short wave
T — Tunable built-in ant.
TA — Table
W — Walnut
X — Projection
+ — Round Screen
* — Plus radio tube complement
** — Total tubes incl. picture tube but excluding rectifiers

1950-51 Television Receiver Specifications

MANUFACTURER	Model	Type	Picture Tube	List Price (Dollars)	Built-in Aerial	Set Also Receives	Record Player	Cabinet Finish	Mfr's. Chassis No.	Total Tubes**	Total Rectifiers	IF Frequency	Aurlio Output (watts)	Speaker Size & Type
Motorola (Continued from page 95)														
	19K4	C	19AP4A	399.95	N			MA, BL	TS101	18	2	21.9 I	2	EM 8
	20F1	C	20DP4	575.00	N	AM, FM	RC3	MA, BL	TS119	18	2	21.9 I	2	PM 12
Multiple Television Mfg. Co., 927 Hegegan Ave., Brooklyn 8, N. Y.	L-16W	CT	16DP4	269.95				MA, BL	K2	27	4	21.25 S	4	PM 12
	LFD-15	C	16DP4	299.95				MA, BL	K2	27	4	21.25 S	4	PM 12
	TT7-19	TA	16DP4	329.00				MA, BL	K2	27	4	21.25 S	4	PM 12
	L-19	CT	16DP4	369.00				MA, BL	K2	27	4	21.25 S	4	PM 12
	LFD-19	C	16DP4	399.00				MA, BL	K2	27	4	21.25 S	4	PM 12
	19" Remote	CU	16DP4	499.00				MA, BL	K2	27	4	21.25 S	4	PM 12
National Co., Inc., 61 Sherman St., Malden, Mass.	NCTV-1201	TA	12LP4	189.95	N			MA	TV12C	21	2	21.25 I	2	PM 4x6
	NCTV-1225	CT	12LP4	229.95	T			MA	TV12C	21	2	21.25 I	2	PM 10
	NCTV-1601	TA	16RP4	249.95	T			MA	TV16C	21	2	21.25 I	2	PM 4x6
	NCTV-1602	TA	16RP4	259.95	T			BL	TV16C	21	2	21.25 I	2	PM 10
	NCTV-1625	CT	16RP4	369.95	T			MA	TV16C	21	2	21.25 I	2	PM 10
	NCTV-1628	CT	16AP4	289.95	T			MA	TV16C	21	2	21.25 I	2	PM 10
	NCTV-1627	GT	16AP4	299.95	T			BL	TV16C	21	2	21.25 I	2	PM 10
North American Philips Co., Inc., 100 E. 42nd St., New York 17, N. Y.	IRVINGTON	C	3NP4X	349.50	N			MA	PC50	20	3	21.25 I	3	PM 8
	MT. VERNON	C	3NP4X	429.50	N			MA	PC50	20	3	21.25 I	3	PM 8
	JUMBO VUE-1200	CO	3NP4X	850.00				M	PC75T	27	4	21.25 S	3	EM 12
	JUMBO VUE-588	CO	3NP4X	599.50				MP	PC75T	27	4	21.25 S	3	EM 12
Olympic Radio & Television, Inc., 34-01—38th Ave., Long Island City, N. Y.	DIPLOMAT	TA	19FP4	369.95	T		PC	MA, BL		20	3			PM 10
	CHALLENGER	CT	16KP4	219.95				MA		17	3			
	RIVIERA	TA	16KP4	239.95				MA		17	3			
	SHANGRI-LA	C	16DP4	569.95	T	FM, AM	RC3	MA, BL		20*	3			PM 12
	BROADMOOR	C	16KP4	319.95				MA, BL		17	3			PM 10
	CATALINA	C	16KP4	449.95		FM, AM	RC3	MA, BL		17*	3			PM 12
	MONTE CARLO	C	16KP4	289.95				MA		17	3			PM 10
	PRESIDENT	C		399.95				MA						
	GOVERNOR	C		179.95				MA						
	ELDORADO	TA		499.95				MA						
Packard-Bell Co., 12333 W. Olympic Blvd., Los Angeles 64, Calif.	2001-TV	TA	12KP4	199.95	N			MA	2001-2	16	3	20.5 I	3.0	PM 6
	2002-TV	C	12KP4	239.95	N			MA, BL, MP	2001-2	16	3	20.5 I	3.0	PM 6
	2601-TV	C	16LP4	359.95	N			MA, BL, MP	2601	23	3	20.5 S	4.5	PM 12
	2202-TV	TA	16TP4	249.95	N			MA, BL, MP	2201-4	17	3	20.5 S	2.7	PM 6
	2204-TV	TA	16TP4	299.95	N			MA, BL, MP	2201-4	17	3	20.5 S	2.7	PM 6
	2891-TV	C	16TP4	449.95	N	AM, FM	RC3	WA, MA, BL, MP	2801	23	4	20.5 I	4.0	PM 12
	2803	C	19AP4	499.95	N			WA, MA, BL, MP	2803	23	4	20.5 I	4.0	PM 12
	2301	C	19AP4	379.95	N			WA, MA, BL, MP	2301	19	3	20.5 I	4.0	PM 10
	2101	TA	16TP4	219.95	N			MA, BL	2101-2	17	3	20.5 I	2.7	PM 6.5
	2102	C	16TP4	299.95	N			MA, BL, MP	2101-2	17	3	20.5 I	2.7	PM 10
	2105A	C	16TP4	259.95	N			WA, MA, O	2105	17	3	20.5 I	2.7	PM 6.5
	2105	C	16TP4	259.95	N			WA, MA, O	2101-2	17	3	20.5 I	2.7	PM 10
	2602	C	16TP4	399.95	N	AM, FM	RC3	WA, MA, BL, MP	2101-2	22	3	20.5 I	2.7	PM 10
	Pathé Television Corp., 250 W. 57th St., New York 19, N. Y.	16-21	C	16RP4	259.50	N			MA	703-10	17	2	23.0 I	5
16-22		C	16RP4	339.50	N			MA	703-10	17	2	23.0 I	5	PM 10
16-25		TA	16RP4	299.50	N			MA	703-10	17	2	23.0 I	5	PM 10
12-2		TA	12LP4	169.50	N			MA	700	17	2	23.0 I	3	PM 5
Philco Corp., C & Tinea Sts., Philadelphia 34, Pa.	1207	TA	12 $\frac{1}{2}$ "	169.95	T			MA, PL		17	2	22.1 I	1	PM 4
	1208	TA	12 $\frac{1}{2}$ "	189.95	T			MA, PL		17	2	22.1 I	1	PM 5
	1234	C	12 $\frac{1}{2}$ "	229.95	T			MA		17	2	22.1 I	1	PM 8
	1222	TA	12 $\frac{1}{2}$ "	269.95	T		RC3	MA		17	2	22.1 I	1	EM 8x9
	1443B	CT	14CP4	219.95	T			MA		19	3	22.1 I	3	PM 6
	1443M	TA	14CP4	239.95	T			MA		19	3	22.1 I	3	PM 6
	1443L	TA	14CP4	259.95	T			MA		19	3	22.1 I	3	PM 6
	1443X	C	14CP4	279.95	T			BL		19	3	22.1 I	3	PM 6
	1443XL	C	14CP4	299.95	T			MA		19	3	22.1 I	3	PM 10
	1443PW	C	14CP4	359.95	T	AM	RC3	WA		22	3	22.1 I	5	EM 6x9
	1443PM	C	14CP4	379.95	T	AM	RC3	MA		22	3	22.1 I	5	EM 6x9
	1443PL	C	14CP4	399.95	T	AM	RC3	BL		22	3	22.1 I	5	EM 6x9
	1601	TA	16WP4	219.95	T			M		19	4	22.1 I	3	PM 6
	1601T	CT	16WP4	239.95	T			MA		19	4	22.1 I	3	PM 6
	1602	TA	16WP4	259.95	T			MA		19	4	22.1 I	3	PM 6
	1604M	TA	16WP4	269.95	T			MA		20	5	22.1 I	3	PM 6
	1604L	TA	16WP4	289.95	T			BL		20	5	22.1 I	3	PM 8
	1606	TA	16WP4A	269.95	T			MA		20	5	22.1 I	3	PM 10
	1634M	C	16WP4A	299.95	T			MA		20	5	22.1 I	3	PM 10
	1634L	C	16WP4A	319.95	T			BL		20	5	22.1 I	3	PM 10
	1636M	C	17BP4A	359.95	T			MA		21	4	22.1 I	5	PM 12
	1636L	C	17BP4A	379.95	T			BL		21	4	22.1 I	5	PM 12
	1638	C	17BP4A	449.95	T			MA		21	4	22.1 I	5	PM 12
	1670	C	17BP4A	379.95	T			RC3	MA	19	4	22.1 I	5	EM 6x11
	1672	C	17BP4A	429.95	T	AM	RC3	MA		22	4	22.1 I	5	EM 6x11
	1674M	C	17BP4A	479.95	T	AM	RC3	MA		22	4	22.1 I	5	EM 6x11
	1674L	C	17BP4A	499.95	T	AM	RC3	BL		22	4	22.1 I	5	EM 6x11
	1675	C	17BP4A	549.95	T	AM, FM	RC3	MA		24	4	22.1 I	5	EM 6x11
	1676	C	173P4	599.95	T	AM, FM	RC3	MA		26	4	22.1 I	5	EM 6x11
	2134	C	20DP4A	429.95	T			MA		21	4	22.1 I	5	PM 10
	2136	C	20DP4A	479.95	T			MA		21	4	22.1 I	5	PM 12
	2138	C	20DP4A	575.00	T			MA		21	4	22.1 I	5	PM 12
2175	C	20DP4A	695.00	T	AM, FM	RC3	MA		26	4	22.1 I	5	PM 12	
2176	C	20DP4A	750.00	T	AM, FM	RC3	MA		26	4	22.1 I	5	PM 12	
Pilot Radio Corp., 37-06—38th St., Long Island City 1, N. Y.	TV-127	TA	12LP4A	239.50	T	FM		MA		24	4	21.25 I	2	PM 6
	TV-163	TA	16KP4	299.50	T	FM		MA		25	4	21.25 I	2.5	PM 8
	TV-166	C	16GP4	399.50	T	FM		MA		25	4	21.25 I	2.5	PM 12
RCA Victor Div., Radio Corp. of America, Camden 2, N. J.	SHELBY	TA	12LP4	179.95	N			M	KCS45	20	3	S	5	EM 5x7
	CUMBERLAND	C	12LP4	209.95	N			MA, WA	KCS45A	20	3	S	5	PM 8
	CUMBERLAND	C	12LP4	219.95	N			LO	KCS45A	20	3	S	5	PM 8
	SOMERVILLE	C	12LP4	329.50	N	AM	RC3	MA, WA	KCS46, RK156	24	4	S	6	PM 12
	SOMERVILLE	C	12LP4	339.50	N	AM	RC3	LO	KCS46, RK156	24	4	S	6	PM 12
	NEWPORT	TA	16GP4	219.95				M	KCS47	20	2	S	3.5	PM 8
	KENT	CT	16GP4	249.95				M	KCS47	20	2	S	3.5	PM 8
	KINGSBURY	C	16GP4	279.95	N			MA, WA	KCS47A	20	2	S	3.5	PM 12
	KINGSBURY	C	16GP4	299.95	N			LO	KCS47A	20	2	S	3.5	PM 12
	HIGHLAND	C	16GP4	299.95	N			MA, WA	KCS47A	20	2	S	3.5	PM 12
	HIGHLAND	C	16GP4	319.95	N			LO	KCS47A	20	2	S	3.5	PM 12
	FAIRFIELD	C	16GP4	329.50	N			MA, WA	KCS47A	20	2	S	3.5	PM 12
	FAIRFIELD	C	16GP4	349.50	N			LO	KCS47A	20	2	S	3.5	PM 12
	REGENCY	C	16GP4	359.50	N			MA, WA	KCS47A	20	2	S	3.5	PM 12
	MODERN	C	16GP4	369.50	N			MA, WA, LO	KCS47A	20	2	S	3.5	PM 12

1950-51 Television Receiver Specifications

MANUFACTURER	Model	Type	Picture Tube	List Price (Dollars)	Built-in Aerial	Set Also Receives	Record Player	Cabinet Finish	Mfr's Chassis No.	Total Tubes**	Total Rectifiers	IF Frequency	Audio Output (watts)	Speaker Size & Type	
Bendix Radio Div., Bendix Aviation Corp., Towson 4, Md.	2051	TA	14BP4	169.95	N	MA	T5-4	13	2	21.5 I	1.5	PM 4x6	
	2051	CT	14BP4	199.95	N	MA	T5-4	13	2	21.5 I	1.5	PM 8	
	2060	TA	16RP4	239.95	N	MA	T5-3	13	2	21.5 I	1.5	PM 4x6	
	6001	C	16RP4	299.95	N	MA	T5-2	13	2	21.5 I	1.5	PM 10	
	6002	CT	16RP4	279.95	N	MA	T5-2	13	2	21.5 I	1.5	PM 10	
	6100	C	16RP4	399.95	N	AM, FM	RC3	MA	T5-2, C16-1	13, 6	2, 1	21.5 I	1.5	PM 10	
Bowers Television Co., P.O. Box 1262, Reading, Pa.	TC17-30	C	17XP4A	600.00		FM	MA, BL	630K-2	25	3	25.75 S	4	PM 10	
Brunswick Div., Radio & Television, Inc., 244 Madison Ave., New York 16, N.Y.	MARLOWE	TA	16XP4	189.95	N	MA	616	17	2	I	3	PM 5	
	GLASGOW	CT	16XP4	219.95	N	MA	6161	17	2	I	3	PM 10	
	KENSINGTON	C	16XP4	249.95	N	MA	1116	17	2	I	3	PM 10	
Capehart-Farnsworth Corp., 3700 E. Postle, Fl. Wayne 1, Ind.	SPINET	C	16RP4	299.95	T	MA	CX-33	20	2	26.25 I	2.5	PM 8	
	NANTUCKET	TA	16RP4	279.95	T	MA	CX-33	20	2	26.25 I	2.5	PM 8	
	BEOFFORD	TA	16RP4	269.95	T	BL	CX-33	20	2	26.25 I	2.5	PM 8	
	MONMOUTH	C	16RP4	339.95	T	MA	CX-33	20	2	26.25 I	2.5	PM 12	
	GEORGETOWN	C	16GP4	379.95	T	MA	CX-33	20	2	26.25 I	2.5	PM 6x8	
	VIRGINIAN	C	17AP4A	369.95	T	MA	CX-33	20	2	26.25 I	2.5	PM 12	
	NEW ENGLANDER	C	16RP4	399.95	T	BL	CX-33	20	2	26.25 I	2.5	PM 12	
	TICONDEROGA	C	16RP4	650.00	T	AM	RC3	MA	CX-33	22	3	26.25 I	10	PM 12	
	SARATOGA	C	17AP4A	650.00	T	AM, FM	RC3	MA	CX-33	22	3	26.25 I	10	PM 12	
	CHICAGOAN	C	16GP4	349.95	T	MA	CX-33	20	2	26.25 I	2.5	PM 12	
	CHICAGOAN	C	16GP4	369.95	T	BL	CX-33	20	2	26.25 I	2.5	PM 12	
	WILLIAM PENN	C	16GP4	399.95	T	MA	CX-33	20	2	26.25 I	2.5	PM 12	
	NEW AMSTERDAM	C	19AP4A	650.00	T	AM, FM	RC3	MA	CX-33	22	3	26.25 I	10	PM 12	
Conrac, Inc., 649 W. Foothill Blvd., Glendale, Calif.	16M36	C	16GP4	369.95	N	MA, MP, BL, WA	36	21	3	25.75 S	5	PM 12	
	17P29	C	19AP4A	459.95	N	MA, MP, BL	39	21	3	25.75 S	5	PM 12	
Crosby Div., Avco Corp., 1529 Arlington St., Cincinnati, Ohio	11-641	CT	12LP4A	259.95	N	PC	MA	18	2	I	1.5	PM 10
	11-651-WU	CT	12LP4A	269.95	N	PC	WA	18	2	I	1.5	PM 10
	11-471-BU	CT	12LP4A	259.95	N	PC	BL	18	2	I	1.5	PM 10
	11-642	TA	17SP4	259.95	N	PC	MA	21	3	I	2.0	EM 5
	11-672-BU	TA	17SP4	279.95	N	PC	BL	21	3	I	2.0	PM 10
	11-643-MU	C	19AP4A	417.95	N	PC	MA	21	3	I	2.0	PM 10
	11-645-MU	C	17SP4	469.95	N	AM	RC3	MA	28	4	I	2.0	PM 10	
	11-674-BU	C	17SP4	469.95	N	AM	RC3	BL	28	4	I	2.0	PM 10	
	11-645	C	16TP4	299.95	N	PC	MA	21	3	I	2.0	PM 10
	11-655	C	16TP4	269.95	N	PC	WA	21	3	I	2.0	PM 10
	11-475	C	16TP4	319.95	N	PC	BL	21	3	I	2.0	PM 10
	11-648	C	16GP4	339.95	N	PC	MA	21	3	I	2.0	PM 10
	11-476	C	16GP4	359.95	N	PC	BL	21	3	I	2.0	PM 10
	11-493	C	17BP4	349.95	N	PC	MA	21	3	I	2.0	PM 10
	11-493	C	17BP4	369.95	N	PC	BL	21	3	I	2.0	PM 10
	11-447	C	16TP4	369.95	N	PC	MA	21	3	I	2.0	PM 10
	11-477	C	16TP4	459.95	N	PC	BL	21	3	I	2.0	PM 10
	11-460	C	17BP4	399.95	N	PC	MA	21	3	I	2.0	PM 10
11-470	C	17BP4	419.95	N	PC	BL	21	3	I	2.0	PM 10	
11-458	C	19AP4A	449.95	N	PC	MA	21	3	I	2.0	PM 10	
11-484	C	19AP4A	469.95	N	PC	BL	21	3	I	2.0	PM 10	
11-454	C	19AP4A	469.95	N	PC	MA	21	3	I	2.0	PM 10	
11-459	TA	16TP4	249.95	N	PC	MA	21	3	I	2.0	PM 5	
DeWald Radio Mfg. Corp., 35-15 37th Ave., Long Island City 1, N. Y.	DT1000	TA	16SP4	169.95	N	WA	1020	20	3	25.75 I	4.2	EM 6.1	
	DT1000	TA	16SP4	179.95	N	MA	1030	20	3	25.75 I	4.2	EM 6.5	
	ET140	TA	14CP4	219.95	N	MA	160	20	3	25.75 I	4.2	EM 6.7	
	ET141	C	14CP4	269.95	N	MA	141	20	3	25.75 I	4.2	EM 10	
	DT162	TA	16GP4	269.95	N	MA	162	20	3	25.75 I	4.2	EM 6.5	
	DT163	C	16GP4	299.95	N	MA	163	20	3	25.75 I	4.2	EM 10	
	DT190	C	19SP4	369.95	N	MA	190	20	3	25.75 I	4.2	EM 10	
DuMont Laboratories, Inc., Allen B., 35 Market St., E. Paterson, N. J.	SHERBROOKE	C	19AP4	745.00	..	AM, FM, SW	RC3	MA, BL	RA109A	34	4	26.25 S	4.5	PM 10	
	HANOVER	C	19AP4	699.95	..	AM, FM, SW	MA, BL	RA109A	30	4	26.25 S	4.5	PM 10	
	MT, VERNON	C	19AP4	499.95	..	FM, SW	MA, BL	RA112A	22	3	26.25 S	2	PM 10	
	WESTERLY	C	19AP4	469.95	..	FM, SW	MA, BL	RA112A	22	3	26.25 S	2	PM 10	
	ARMORE	C	19AP4	439.95	..	FM, SW	MA, BL	RA112A	22	3	26.25 S	2	PM 10	
	TARRYTOWN	C	17AP4	630.00	..	AM, FM, SW	RC3	MA, BL	RA113B	27	4	26.25 S	2	PM 12	
	BURLINGAME	C	17AP4	429.95	..	FM, SW	MA, BL	RA113B	22	3	26.25 S	2	PM 10	
	REVERE	C	17AP4	439.95	..	FM, SW	MA, BL	RA113B	22	3	26.25 S	2	PM 10	
	BROOKVILLE	C	17AP4	389.95	..	FM, SW	MA, BL	RA113B	22	3	26.25 S	2	PM 10	
	ANDOVER	C	17AP4	MA, BL	RA117A	20	2	26.25 S	2	PM 10	
	PARK LANE	C	17AP4	MA, BL	RA117A	20	2	26.25 S	2	PM 10	
	STRATHMORE	C	17AP4	MA, BL	RA117A	20	2	26.25 S	2	PM 10	
	CARLTON	TA	17AP4	M	RA117A	20	2	26.25 S	2	PM 5	
	VENTURA	TA	17AP4	M	RA117A	20	2	26.25 S	2	PM 5	
	SUMTER	TA	17AP4	M	RA117A	20	2	26.25 S	2	PM 5	
	WESTMINSTER II	C	17AP4	AM, FM, SW	RC3	MA	RA116A-1	42	5	26.25 S	6	PM 12	
	Emerson Radio & Phono- graph Corp., 111 Eighth Ave., New York 11, N. Y.	673	TA	12LP4A	189.95	N	MA	120133B	15	2	25.75 I	3	EM 6
673		TA	12LP4A	199.95	N	BL	120133B	15	2	25.75 I	3	EM 6	
660		TA	12LP4A	199.95	N	MA	120133B	15	2	25.75 I	3	EM 6	
662		TA	14BP4	199.95	N	PL	120127B	17	4	25.75 I	4	PM 5	
661		TA	16GP4	259.95	N	MA	120134B	18	4	25.75 I	5	PM 8	
663		TA	16RP4	249.95	N	MA	120129B	17	4	25.75 I	4	PM 5	
665		C	12LP4A	329.95	N	AM	RC3	MA	120131B	21	3	25.75 I	3	EM 12	
664		C	12LP4A	229.95	N	MA	120133B	15	2	25.75 I	3	EM 12	
664		C	12LP4A	239.95	N	BL	120133B	15	2	25.75 I	3	EM 12	
668		C	16GP4	299.95	N	MA	120134B	18	4	25.75 I	5	PM 12	
668		C	16GP4	299.95	N	BL	120134B	18	4	25.75 I	5	PM 12	
667		C	16GP4	329.95	N	MA	120134B	18	4	25.75 I	5	PM 12	
667		C	16GP4	349.95	N	BL	120134B	18	4	25.75 I	5	PM 12	
669		C	19AP4	429.95	N	MA	120129B	18	4	25.75 I	5	PM 12	
669	C	19AP4	459.95	N	BL	120129B	18	4	25.75 I	5	PM 12		
666	C	16GP4	429.95	N	AM, FM	RC3	MA	120135B	26	4	25.75 I	4	PM 12		
Fada Radio & Electric Co., 525 Main St., Belleville, N. J.	S4T15	TA	14BP4	199.95	N	MA	677	19	3	25.75 I	3.2	PM 6	
	S4C20	C	14BP4	239.95	N	MA	677	19	3	25.75 I	3.2	PM 10	
	S4T30	TA	14BP4	209.95	N	MA	677	19	3	25.75 I	3.2	PM 6	
	S1005	C	16RP4	299.95	N	MA	677	19	3	25.75 I	3.2	PM 10	
	S1005X	C	16GP4	299.95	N	MA	677	19	3				

1950-51 Television Receiver Specifications

MANUFACTURER	Model	Type	Picture Tube	List Price (Dollars)	Built-in Aerial	Set Also Receives	Record Player	Cabinet Finish	Mfr's. Chassis No.	Total Tubes**	Total Rectifiers	IF Frequency	Audio Output (watts)	Speaker Size & Type
Fada (Continued from page 93)														
	S4C40	C	14BP4	269.95
	S9C10	C	19"	399.95
Federal Television Corp., 137 Duane St., New York 13, N. Y.	631A	CT	16DP4A	399.50	T	MA, BL, EB, WA	27	3	25.75 S	4	PM 12
	632B	CT	19DP4A	499.50	T	WA, MA, BL, EB	27	3	25.75 S	4	PM 12
	633A	C	16DP4A	699.50	T	AM-FM	RC3	WA, MA, BL, EB	27	3	25.75 S	4	PM 12
	634B	C	19DP4A	799.50	T	AM-FM	RC3	WA, MA, BL, EB	27	3	25.75 S	4	PM 12
Freed Radio Corp., 200 Hudson St., New York 13, N. Y.	54	C	16GP4	429.00	T	PC	MA	CHT-1620C	26	2	25.75 S	4.5	PM 12
	55	C	16GP4	399.00	T	MA	CHT-1620C	26	2	25.75 S	4.5	PM 12
	56	C	16GP4	429.00	T	BL	CHT-1620C	26	2	25.75 S	4.5	PM 12
	68	C	16GP4	449.00	T	MA	CHT-1620C	26	2	25.75 S	4.5	PM 12
	101	C	19AP4A	595.00	T	FM	PC	MA	CHT-1900	28	2	25.75 S	4.5	EM 12
	103	C	19AP4A	549.00	T	FM	PC	MA	CHT-1900	28	2	25.75 S	4.5	EM 12
	104	C	19AP4A	595.00	T	FM	PC	BL	CHT-1900	28	2	25.75 S	4.5	EM 12
General Electric Co., Electronics Park, Syracuse, N. Y.	14T2	TA	14CP4	199.95	N	MA	14T2	19	2	41.25 I	2.5	EM 8
	14T3	TA	14CP4	219.95	N	BL	14T3	19	2	41.25 I	2.5	EM 8
	16T3	TA	16KP4	239.95	N	MA	16T3	19	2	41.25 I	2.5	EM 8
	16T4	TA	16KP4	259.95	N	BL	16T4	19	2	41.25 I	2.5	EM 8
	14C102	C	14CP4	239.95	N	MA	14C102	19	2	41.25 I	2.5	EM 12
	14C103	C	14CP4	259.95	N	BL	14C103	19	2	41.25 I	2.5	EM 12
	16C113	C	16KP4	299.95	N	MA	16C113	19	2	41.25 I	2.5	EM 12
	16C116	C	16KP4	299.95	N	MA	16C116	19	2	41.25 I	2.5	EM 12
	19C105	C	19AP4A	439.95	N	MA	19C105	24	4	41.25 I	7.0	EM 12
	19C106	C	19AP4A	459.95	N	BL	19C106	24	4	41.25 I	7.0	EM 12
	16K1	C	16KP4A	469.95	N	AM, FM	RC3	MA	16K1	26	2	41.25 I	2.5	EM 12
	16K2	C	16KP4A	469.95	N	AM, FM	RC3	BL	16K2	26	2	41.25 I	2.5	EM 12
Grem Engineering Co., 206 8th Ave., Brooklyn 15, N. Y.	256-L	C	16KP4	T	AM	M	256	33	3	25.75 S	3.5	PM 12
Hallcrafters Co., The, 4401 W. Fifth Ave., Chicago 24, Ill.	815	TA	16"	249.95	N	MA	18	3	21.25 I	2.5	PM
	811	TA	16"	269.95	N	AM	MA	21	3	21.25 I	2.5	PM
	822	C	16"	299.95	N	MA	18	3	21.25 I	2.5	PM
	818	C	16"	329.95	N	AM	MA	21	3	21.75 I	2.5	PM
	853	C	16"	399.95	N	AM	RC3	MA	21	3	21.25 I	2.5	PM
	870	C	17"	319.95	N	MA	18	3	21.25 I	2.5	PM
	871	C	17"	319.95	N	BL	18	3	21.25 I	2.5	PM
	820	C	17"	349.95	N	AM	MA	21	3	21.25 I	2.5	PM
	821	C	17"	379.95	N	AM	BL	21	3	21.25 I	2.5	PM
	860	C	17"	449.50	N	AM	RC3	MA	21	3	21.25 I	2.5	PM
	861	C	17"	489.50	N	AM	RC3	BL	21	3	21.25 I	2.5	PM
	880	C	19"	379.95	N	MA	18	3	21.25 I	2.5	PM
	890	C	20"	595.00	N	AM, FM	RC3	MP	25	4	21.25 I	2.5	PM
	894	C	20"	595.00	N	AM, FM	RC3	MA	25	4	21.25 I	2.5	PM
	898	C	20"	595.00	N	AM, FM	RC3	BL	25	4	21.25 I	2.5	PM
	809	TA	16"	199.95	N	MA	1.0	PM
	810	TA	16"	229.95	N	MA
	805	C	16"	279.95	N	MA
	806	C	16"	295.00	N	BL
Hoffman Radio Corp., 3761 S. Hill St., Los Angeles 7, Calif.	630	TA	14CP4	229.95	T	BL, MA	170	18	3	26.1 S	3	PM 8
	631	TA	14CP4	219.95	T	BL, MA	170	18	3	26.1 S	3	PM 8
	870, 871, 872	CT	14CP4	279.95	T	BL, MA, MP	170	18	3	26.1 S	3	PM 12
	634	TA	16TP4	269.95	T	BL, MA	171	18	3	26.1 S	3	PM 6x12
	635	TA	16TP4	249.95	T	BL, MA	171	18	3	26.1 S	3	PM 6x12
	867	C	16TP4	349.95	T	BL, MA, MP	171	18	3	26.1 S	3	PM 12
	866, 868	C	16TP4	369.95	T	BL, MA, MP	171	18	3	26.1 S	3	PM 12
	877	C	16TP4	319.95	T	BL, MA, MP	171	18	3	26.1 S	3	PM 12
	876, 878	C	16TP4	339.95	T	BL, MA, MP	171	18	3	26.1 S	3	PM 12
	951	C	16TP4	459.95	T	AM, FM	RC3	BL, MA, MP	172	21	3	26.1 S	3	PM 12
	950, 952	C	16TP4	479.95	T	AM, FM	RC3	BL, MA, MP	172	21	3	26.1 S	3	PM 12
	867A	C	16TP4	349.95	T	BL, MA, MP	173	18	3	26.1 S	3	PM 12
	866A, 868A	C	16TP4	369.95	T	BL, MA, MP	173	18	3	26.1 S	3	PM 12
	950A	C	16TP4	479.95	T	AM, FM	RC3	BL, MA	174	21	3	26.1 S	3	PM 12
	951A	C	16TP4	459.95	T	AM, FM	RC3	BL, MA	174	21	3	26.1 S	3	PM 12
	890	C	19AP4	439.95	T	BL, MA	175	18	3	26.1 S	3	PM 12
	891	C	19AP4	419.95	T	BL, MA	175	18	3	26.1 S	3	PM 12
	892	C	19AP4	439.95	T	BL, MA	175	18	3	26.1 S	3	PM 12
	960	C	19AP4	575.00	T	AM, FM	RC3	BL, MA	176	23	4	25.1 S	10	PM 12
	961	C	19AP4	550.00	T	AM, FM	RC3	BL, MA	176	23	4	25.1 S	10	PM 12
Hertner Electric Co., 12690 Elmwood Ave., Cleveland 11, Ohio	L-10	CO	5TP4X	1850.00	MA	L-10	32	7	25.75 S	20	PM 12
Industrial Television, Inc., 359 Lexington Ave., Clifton, N. J.	248	C	16FP4A	379.00	MA, BL	IT-35R	25	4	25.75 S	7	EM 12
	348	C	19AP4A	469.00	MA, BL	IT-35R	25	4	25.75 S	7	EM 12
	761	T	16TP4	229.00	MA, BL	IT-61R-2	18	2	21.25 I	3	PM 8
	1161	C	16TP4	299.00	MA, BL	IT-61R-2	18	2	21.25 I	3	PM 12
	1261	C	16TP4	319.00	MA, BL	IT-61R-2	18	2	21.25 I	3	PM 12
	1361	C	19DP4A	379.00	MA, BL	IT-61R-5	18	2	21.25 I	3	PM 12
International Television Corp., 238 William St., New York 7, N. Y.	ROYAL	TA	16RP4	229.95	N	PC	MA, BL, LO	F18	18	2	I	4.5	PM 4x6
	IMPERIAL	CT	16DP4	269.95	N	PC	MA, BL, LO	F18	18	2	I	4.5	PM 12
	MONARCH	C	16RP4	299.95	N	PC	MA, BL, LO	F18	18	2	I	4.5	PM 12
	PRESIDENT	C	16RP4	319.95	N	PC	MA, BL, LO	F18	18	2	I	4.5	PM 12
	EMPEROR	CT	19AP4	339.95	N	PC	MA, BL	F19	18	2	I	4.5	PM 12
Jackson Industries, Inc., 500 E. 40th St., Chicago 15, Ill.	14T	TA	12LP4	179.95	N	MA	19	2	25.75 I	2.5	PM 8
	16T	TA	16"	199.95	N	MA	19	2	25.75 I	2.5	PM 8
	16C	C	16"	229.95	N	MA	19	2	25.75 I	2.5	PM 10
	29C	C	19"	349.95	N	MA	19	2	25.75 I	2.5	PM 10
	316	C	16"	349.95	N	AM	RC3	MA	19	2	25.75 I	2.5	PM 10
Kaye-Halbert Corp., 3555 Hayden Ave., Culver City, Calif.	231W	TA	16	229.95	N	241	21	3	I	3	PM 6
	231M	TA	16	239.95	N	241	21	3	I	3	PM 6
	231B	TA	16	249.95	N	241	21	3	I	3	PM 6
	232W, 232M	TA	16	279.95	N	241	21	3	I	3	PM 6
	232B	TA	16	289.95	N	241	21	3	I	3	PM 6
	233W	C	16	289.95	N	241	21	3	I	3	PM 12
	233M	C	16	299.95	N	241	21	3	I	3	PM 12

(Continued on next page)

BL — Blond	CU — Custom	L — Leatherette	N — Non-tunable built-in ant.	RC3 — 3-speed record changer	W — Walnut
C — Console	EB — Ebony	LO — Lined Oak	O — Oak	S — Split sound IF system	X — Projection

1950-51 Television Receiver Specifications

MANUFACTURER	Model	Type	Picture Tube	List Price (Dollars)	Built-in Aerial	Set Also Receives	Record Player	Cabinet Finish	Mfr's Chassis No.	Total Tubes**	Total Rectifiers	IF Frequency	Audio Outpu. (watts)	Speaker Size & Type
*Sage-Haber (Continued from page 94)														
	2339	C	16	309.95	N				241	21	3	1	3	PM 12
	234W	C	16	369.95	N				241	21	3	1	3	PM 12
	234V	C	16	379.95	N				241	21	3	1	3	PM 12
	234B	C	16	389.95	N				241	21	3	1	3	PM 12
	235	C	16	389.95	N				241	21	3	1	3	PM 12
	236	C	16	389.95	N				241	21	3	1	3	PM 12
	237	C	16	399.95	N				241	21	3	1	3	PM 12
	238W	C	19	379.95	N				241	21	3	1	3	PM 12
	238M	C	19	349.95	N				241	21	3	1	3	PM 12
	238S	C	19	399.95	N				241	21	3	1	3	PM 12
	239W	C	19	449.95	N				241	21	3	1	3	PM 12
	239M	C	19	459.95	N				241	21	3	1	3	PM 12
	239B	C	19	459.95	N				241	21	3	1	3	PM 12
	240	C	19	459.95	N				241	21	3	1	3	PM 12
	241	C	19	449.95	N				241	21	3	1	3	PM 12
Magnavox Co., Buster Rd., Fl. Wayne 4, Ind.	HAMPSHIRE	TA	16RP4	155.50	N			MA	CT275	18	2	21.25 I	...	PM 8
	BILTMORE	TA	16TP4	259.50	N			MA	CT272	18	2	21.25 I	...	PM 12
	METROPOLITAN	TA	16TP4	249.50	N			MA, BL	CT272	18	2	21.25 I	...	PM 8
	PLAYHOUSE	CT	16TP4	299.50	T			MA, BL	CT277	18	2	21.25 I	...	PM 12
	S'VOREHAM	CT	16TP4	339.50	T			MA, BL, MP	CT274	18	2	21.25 I	...	PM 12
	CONTEMPORARY	CT	18AP4	355.00	T			MA, BL	CT274	18	2	21.25 I	...	PM 12
	WEDGEWOOD	C	16TP4	459.50	T	AM, FM	RC3	MA, BL	CT275	22	3	21.25 S	3.5	PM 12
	PROVINCIAL	C	16TP4	495.00	T	AM, FM	RC3	MA	CT273	22	3	21.25 I	10	EM 12
	AMERICAN MODERN	C	16TP4	549.00	T	AM, FM	RC3	MA, BL	CT275	22	3	21.25 I	18	EM 15
	FRENCH PROVINCIAL	C	16TP4	595.00	T	AM, FM	RC3	MP	CT275	22	3	21.25 I	18	EM 15
	EMMASSY	C	17BP4	775.00	T	AM, FM, SW	RC3	MA	CT288	28	4	21.25 S	20	EM 12
	PLA'A	C	16"	239.50	...			MA
	HEPPELWHITE	C	16"	379.50	...			MA, BL
	NORMANDY	C	16"	379.50	...			BL
	AMER. TRADITIONAL	C	16"	595.00	...	AM, FM	RC3	MA
	WINDSOR IMPERIAL	C	16"	1390.00	...	AM, FM	RC3	MA
Majestic Radio & Television, Inc., 70 Washington St., Brooklyn 1, N. Y.	120	TA	12LP4	149.95	N			L	99	17	2	24.75 I	3	PM 5
	121	TA	12LP4	174.95	N			MA	99	17	2	24.75 I	3	PM 5
	141	TA	14TP4	189.95	N			MA	100	17	2	24.75 I	3	PM 5
	142	TA	14TP4	209.95	N			MA	100	17	2	24.75 I	3	PM 5
	1600	CT	16DP4	239.95	N			MA	100	17	2	24.75 I	3	PM 10
	162	TA	16RP4	199.95	...			L	101	17	2	24.75 I	3	PM 10
	160	TA	16RP4	239.95	...			MA	101	17	2	24.75 I	3	PM 5
	1600	CT	16RP4	269.95	...			MA	101	17	2	24.75 I	3	PM 5
	1605	CT	16TP4	279.95	...			MA	102	17	2	24.75 I	3	PM 10
	1610	C	16GP4	319.95	...			MA	102	17	2	24.75 I	3	PM 10
Mars Television, Inc., 112-33 Colonial Ave., Corona, L. I., N. Y.	VERSAILLES	C	16DP4A	499.95	N			MA, BL, S, LLO	630	28	3	...	4	PM 10
	HAMPTON	C	16DP4A	499.95	N			MA, BL, S, LLO	630	28	3	...	4	PM 10
	ORIENTAL	C	16DP4A	499.95	N			MA, BL, S, LLO	630	28	3	...	4	PM 10
	REGENT	C	16DP4A	529.95	N			MA, BL, S, LLO	630	28	3	...	4	PM 10
	WARWICK	C	16DP4A	529.95	N			MA, BL, S, LLO	630	28	3	...	4	PM 10
	DARTMOUTH	C	18AP4A	1195.00	...	AM, FM	RC3	MA, BL, S, LLO	630	41	4	...	10	PM 12
Mattison Television & Radio Corp., 893 Broadway, New York 3, N. Y.	CHALLENGER	...	16DP4A	249.95	N			PC, MA	T410A	16	2	S	5	PM 12
	CHALLENGER DELUXE	C	16DP4A	349.95	N			PC, MA	633-4	25	4	S	5	PM 12
	CHALLENGER DELUXE	C	18DP4A	399.95	N			PC, MA	633-4	25	4	S	5	PM 12
	CONTINENTAL	C	16DP4A	379.95	N			PC, MA	633-4	25	4	S	5	PM 12
	DIPLOMAT	C	16DP4A	399.95	N			PC, BL	633-4	25	4	S	5	PM 12
	CAROLYN	C	16DP4A	549.95	N			PC, BL	633-4	25	4	S	5	PM 12
	QUADRILLE	C	16DP4A	495.00	N			PC, BL	633-4	25	4	S	5	PM 12
	QUADRILLE	C	18OP4A	549.95	N			PC, BL	633-4	25	4	S	5	PM 12
Meck Industries, Inc., John, Plymouth, Ind.	14M-C	CT	14CP4	229.50	N			MA, BL	14RC-14VC	18	2	26 I	3	PM 8
	14M-T	TA	14CP4	179.50	N			MA	14RC-14RC	18	2	26 I	3	PM 8
	16M-C	CT	16TP4	259.50	N			MA, BL	16RC-16VC	18	2	26 I	3	PM 8
	16M-T	TA	16TP4	219.50	N			MA	16RC-16VC	18	2	26 I	3	PM 8
	X3B	CT	16DP4	299.50	N			MA, BL	16STR	19	2	26 I	3	12 PM
	19-MC	CT	18TP4	349.50	N	AM		MA, BL	...	19*	2	26 I	3	12 PM
	X5PT	CT	16DP4	359.50	N	AM	RC3	MA, BL	...	19*	2	26 I	3	12 PM
Mercury Radio & Television Corp., 839 S. Wabash Ave., Chicago 5, Ill.	6192	C	16"	339.95	N	FM		MA	...	18	3	I	3	PM 10
	6193	C	16"	349.95	N	FM		BL	...	18	3	I	3	PM 10
	6193	C	16"	339.95	N	FM		MP	...	18	3	I	3	PM 10
	6800	C	16"	399.95	N	AM, FM	RC3	WA	...	18	3	I	3	PM 10
	6100	C	16"	419.95	N	AM, FM	RC3	MA	...	18	3	I	3	PM 10
	6800	C	16"	429.95	N	AM, FM	RC3	MP, O	...	18	3	I	3	PM 10
	9101	C	18"	449.95	N	FM		MA, WA	...	18	3	I	3	PM 10
	9101	C	18"	469.95	N	FM		BL	...	18	3	I	3	PM 10
	6111	C	16"	329.95	N	FM		MA	CTV-215A	18	3	21.25 S	3	PM 10
	6114	C	16"	349.95	N	FM		MA, BL, WA	CTV-215A	18	3	21.25 S	3	PM 10
	9114	C	19"	449.95	N	FM		MA	CTV-215A	18	3	21.25 S	3	PM 10
	9114	C	19"	459.95	N	FM		BL	CTV-218A	18	3	21.25 S	3	PM 10
Mitchell Mfg. Co., 2525 Cloydawn Ave., Chicago 14, Ill.	T16-M, T16B	CT	16TP4	269.50	N			MA, BL	YMT	19	1	26 I	3	PM 8
Motocolor, Inc., 4545 W. Augusta Blvd., Chicago 41, Ill.	14T3	TA	14BP4	169.95	N			PL	TS114	13	2	21.9 I	2	EM 6
	14K1	C	14BP4	239.95	N			MA, BL	TS115	13	2	21.9 I	2	EM 6
	17T3	TA	16RP4	199.95	N			MA	TS89	18	2	21.9 I	2	EM 6
	17T1	TA	16RP4	239.95	N			MA, BL	TS89	18	2	21.9 I	2	EM 6
	17T2	TA	16RP4	239.95	N			MA, BL	TS89	18	2	21.9 I	2	EM 6
	17K1	C	16RP4	269.95	N			MA, BL	TS89	18	2	21.9 I	2	EM 8
	17K2	C	16RP4	289.95	N			MA, BL	TS95	18	2	21.9 I	2	EM 8
	17K3	C	16RP4	329.95	N			MA, BL	TS89	18	2	21.9 I	2	EM 8
	17K4	C	16RP4	249.95	N			MA	TS89	18	2	21.9 I	2	EM 8
	17F1	C	16RP4	419.95	N	AM, FM	RC3	MA, BL	TS89	18	2	21.9 I	2	PM 6x9
	17F2	C	16RP4	449.95	N	AM, FM	RC3	WA	TS89	18	2	21.9 I	2	PM 10
	17F3B	C	16RP4	469.95	N	AM, FM	RC3	BL	TS89	18	2	21.9 I	2	PM 10
	17F4	C	16RP4	469.95	N	AM, FM	RC3	MA	TS89	18	2	21.9 I	2	PM 10
	17F5	C	16RP4	399.95	N	AM, FM	RC3	MA, BL	TS89	18	2	21.9 I	2	PM 10
	18K2	C	18AP4A	339.95	N			MA, BL	TS101	18	2	21.9 I	2	EM 8
	18K3	C	18AP4A	379.95	N			MA	TS101	18	2	21.9 I	2	EM 8

(Continued on page 95)

BL — Blond	CU — Custom	L — Leatherette	N — Non-tunable built-in ant.	RC3 — 3-speed record changer	W — Walnut
C — Console	EB — Ebony	O — Oak	S — Split sound IF system	X — Projection	
CH — Chassis	EM — Electromagnetic	M — Metal	SW — Short wave	— — Round Screen	
CO — Commercial	I — Inter-carrier	MA — Mahogany	T — Tunable built-in ant.	* — Plus radio tube complement	
CT — Cassette	K — Kit	MP — Maple	TA — Table	** — Total tubes incl. picture tube but excluding rectifiers	

1950-51 Television Receiver Specifications

MANUFACTURER	Model	Type	Picture Tube	List Price (Dollars)	Built-in Aerial	Set Also Receives	Record Player	Cabinet Finish	Mfr's. Chassis No.	Total Tubes**	Total Rectifiers	IF Frequency	Audio Output (watts)	Speaker Size & Type
RCA (Continued from page 98)														
	PROVINCIAL	C	16GP4	389.50	N	MA, WA, MP	KCS47A	20	2	S	3.5	PM 12
	FAIRFAX	C	16GP4	459.50	N	AM	RC3	MA, WA	KCS48, RK156	25	3	S	6	PM 12
	FAIRFAX	C	16GP4	479.50	N	AM	RC3	LO	KCS48, RK156	25	3	S	6	PM 12
	RUTLAND	C	16GP4	525.00	N	AM, FM	RC3	MA, WA	KCS48, RK156	27	3	S	11	PM 12
	HARTFORD	C	16GP4	575.00	N	AM, FM	RC3	MA, WA	KCS48, RK156	27	3	S	11	PM 12
	HARTFORD	C	16GP4	595.00	N	AM, FM	RC3	LO	KCS48, RK156	27	3	S	11	PM 12
	YORK	TA	19AP4A	349.50	N	MA, WA	KCS49	20	2	S	3.5	PM 8
	YORK	TA	19AP4A	359.50	N	LO	KCS49	20	2	S	3.5	PM 8
	HILLSDALE	C	19AP4A	425.00	N	MA, WA	KCS49A	20	2	S	3.5	PM 8
	HILLSDALE	C	19AP4A	445.00	N	LO	KCS49A	20	2	S	3.5	PM 8
	NORTHAMPTON	C	19AP4A	459.00	N	MA, WA	KCS49A	20	2	S	3.5	PM 8
	SEDGWICK	C	19AP4A	750.00	N	AM, FM	RC3	MA, WA	KCS60, RK156	27	3	S	11	PM 12
Radio Craftsmen, Inc., The 1617 S. Michigan Ave., Chicago 16, Ill.	RC100A	CH	16TP4	230.00	RC100A	25	5	28.1 S
Raytheon Mfg. Co., Belmont Radio Div., 5921 W. Dickens Ave., Chicago, Ill.	ROVER CONSOLETTA CRITERION DICKENS RAMBLER RANGER SILVER ANNIVERSARY MAYFAIR MOZART DEVONSHIRE SAVOY SANTUNG CLAYTON CATALINA ADAMS	TA C C TA TA TA C C C C C C C C	12LP4A 12LP4A 18AP4A 16TP4 16TP4 16TP4 17BP4 17BP4 16TP4 17BP4 17BP4 17BP4 20 P4 20BP4 20BP4	189.95 239.95 299.95 259.95 239.95 249.95 289.95 309.95 329.95 425.00 435.00 449.95 429.95 449.95 625.00	T T T T T T T T T T T T T T T AM AM AM AM, FM RC3 RC3 RC3 RC3	L MA MA MA L L MA LO MA MA MA LO MA LO MA	12AX27 12AX27 18AX23 14AX21 14AX21 14AX21 14AX21 17AY21 17AY21 14AX21 17AY21 17AY21 20AY21 20AY21 20AY21	22.75 22.75 22.75 22.75 22.75 22.75 22.75 22.75 22.75 22.75 22.75 22.75 22.75 22.75	2.5 2.5 2.5 2.5 2.5 2.5 2.5 2.5 2.5 2.5 2.5 2.5 2.5 2.5	PM 6 PM 6 PM 10 PM 6 PM 6 PM 10 PM 6 PM 6 PM 6 PM 12 PM 12 PM 10 PM 12	
Regal Electronics Corp., 603 W. 130th St., New York 27, N. Y.	1230 C031 19C31 16T36 CD36 19C36 22T17 22C17 227 7717 7719 5616 5619	TA TA CT CT TA CT CT TA C CT C CT CT	12LP4 16DP4A 16DP4A 19DP4A 16DP4A 16DP4A 19DP4A 17BP4A 17BP4A 17BP4A 17BP4A 18DP4A 16DP4A 19DP4A	290.50 329.50 360.50 497.50 376.50 415.50 527.50 271.75 345.75 AM, FM AM, FM AM, FM PC PC PC	MA, BL MA, BL MA, BL MA, BL MA, BL MA, BL MA MA MA MA MA MA MA MA	1230 1831 1831 1831 1836 1836 1836	27 27 27 27 32 32 32 20 20 20 20 20 20 20	3 4 4 4 4 4 4 2 2 2 2 2 2	25.75 S 25.75 S 25.75 S 25.75 S 25.75 S 25.75 S 25.75 S 26.1 I 26.1 I 26.1 I 26.1 I 26.1 I 26.1 I	3 3 3 3 3 3 3 3 3 3 3 3 3	PM 5x7 PM 5x7 PM 12 PM 12 PM 5x7 PM 12 PM 12 EM 4x6 EM 12 EM 12 EM 12 EM 12 EM 12
S.M.A. Co., 4721 N. Kedzie Ave., Chicago 25, Ill.	TV-111-A TV-114 TV-117 TV-117	C C C C	16AP4 16AP4 19" 19"	329.95 319.95 449.95 459.95	N N N N	FM FM FM FM	MA MA, BL, WA MA BL	CTV-215A CTV-215A CTV-215A CTV-215A	18 18 18 18	3 3 3 3	21.25 S 21.25 S 21.25 S 21.25 S	3 3 3 3	PM 10 PM 10 PM 12 PM 12
Scott Radio Laboratories, Inc., 4541 Ravenswood Ave., Chicago 40, Ill.	510T 710 910 AC-16 AT-16 AC-14 AT-14	C C C C TA C TA	16TP4 16TP4 20DP4 16TP4 16TP4 14BP4 14BP4	695.00 385.00 485.00 279.00 249.00 239.00 198.00	N N N N N N N	AM, FM	RC3	MA, BL MA MA MA MA MA MA	710 710 910 710 710 410 410	31 18 18 18 18 18 18	3 2 2 2 2 2 2	21.6 I 21.6 I 21.6 I 21.6 I 21.6 I 21.6 I 21.6 I	20 10 10 2 2 2 2	PM 12 PM 12 PM 12 PM 10 PM 10 PM 10 PM 8
Sentinel Radio Corp., 2100 Dempster St., Evanston, Ill.	420-TVM 420-TVB 423-CVM 423-CVB 424-CVM 424-CVB 428-CVM 428-CVB 425-CVM 425-CVB	TA TA C C C C C C C C	16RP4 16RP4 16RP4 16RP4 16RP4 16RP4 16RP4 16RP4 16RP4 16RP4	239.95 249.95 279.95 289.95 319.95 339.95 349.95 369.95 419.95 439.95	T T T T T T T T T T	MA BL MA BL MA BL MA BL MA BL	420 420 423 423 423 423 428 428 425 425	19 19 19 19 19 19 19 19 19 19	2 2 2 2 2 2 2 2 2 2	25.5 I 25.5 I 25.5 I 25.5 I 25.5 I 25.5 I 25.1 I 25.1 I 25.5 I 25.5 I	3 3 3 3 3 3 3 3 3 3	EM 4x6 EM 4x6 PM 10 PM 10 PM 12 PM 12 EM 12 EM 12 EM 12 EM 12
Setchell-Carlson, Inc., New Brighton, Minn.	150 1500 1500 L.P. 150 1500 1500LP	TA C C TA C C	12LP4A 12LP4A 12LP4A 12LP4A 12LP4A 12LP4A	229.00 299.00 299.00 234.00 309.00 269.00	AM AM AM AM AM AM RC3 RC3	MA MA MA BL BL BL	15 15 15 15 15 15	23 23 23 23 23 23	3 3 3 3 3 3	26.1 I 26.1 I 26.1 I 26.1 I 26.1 I 26.1 I	2.5 2.5 2.5 2.5 2.5 2.5	PM 5 PM 10 PM 10 PM 5 PM 10 PM 10
Shevers, Inc., Harold, 123 W. 64th St., New York 23, N. Y.	Q.A CLASSIC BRYANT REGENCY TRAFALGAR BARCLAY DIGBY CHELSEA BARCLAY BRYANT CHELSEA RECTOR(T)	CU CU CU CU CU CU CU CU CU CU CU CU	16BP4A 16BP4A 16BP4A 16BP4A 16BP4A 16BP4A 16BP4A 16BP4A 19AP4A 19AP4A 19AP4A 19AP4A	N N N N N N N N N N N N	MA, MP MA, WA MA, BL, WA MA MA MA, BL, WA MA MA, BL, WA MA, BL, WA MA, BL MA	031A 031A 031A 031A 031A 031A 031A 031A 031A 031A 031A	27 27 27 27 27 27 27 27 27 27 27	4 4 4 4 4 4 4 4 4 4 4	21.25 S 21.25 S 21.25 S 21.25 S 21.25 S 21.25 S 21.25 S 21.25 S 21.25 S 21.25 S 21.25 S	3 3 3 3 3 3 3 3 3 3 3	PM 12 PM 12 PM 12 PM 12 PM 12 PM 12 PM 12 PM 12 PM 12 PM 12 PM 6
Sound Laboratories, 323 E. 48th St., New York 17, N. Y.	PENTHOUSE	CU	16KP4	T	AM, FM	RC3	630S56	38	4	25.75 S	10	PM 12
Spartan Radio-Television 2400 E. Ganson St., Jackson, Mich.	DEXTER MAYWOOD OBSERVER BELMAR GORHAM KENWOOD LYNBROOK ARDMOOR CARNEGIE	TA TA TA TA TA C C C C	12 1/2 12 1/2 16 16 16 12 1/2 16 16 19	169.95 189.95 189.95 249.95 289.95 189.95 299.95 319.95 429.95	MA MA L MA MA MA MA MA MA	19 24 26 26 26 19 26 26 26 *	I S I I I I I I I	PM 10 PM 10 PM 10 PM 10 PM 10 PM 10 PM 10 PM 10 PM 12

(Continued on page 102)

BL — Blond	CU — Custom	L — Leatherette	N — Non-tunable built-in ant.	RC3 — 3-speed record changer	W — Walnut
C — Console	EB — Ebony	LO — Lined Oak	O — Oak	S — Split sound IF system	X — Projection
CH — Chassis	EM — Electromagnetic	M — Metal	PC — Phono Jack	SW — Short wave	+ — Round Screen
CO — Commercial	I — Inter-carrier	MA — Mahogany	PL — Plastic	T — Tunable built-in ant.	* — Plus radio tube complement
CT — Console	K — Kit	MP — Maple	PM — Permanent Magnet	TA — Table	** — Total tubes incl. picture tube but excluding rectifiers

1950-51 Television Receiver Specifications

MANUFACTURER	Model	Type	Picture Tube	List Price (Dollars)	Built-in Aerial	Set Also Receives	Record Player	Cabinet Finish	Mfr's. Chassis No.	Total Tubes**	Total Rectifiers	IF Frequency	Audio Output (watts)	Speaker Size & Type
Spartan (Continued from page 99)														
	NASSAU	C	16	459.95	..	AM, FM	RC3	MA	26		I	...	PM 12
	WESTMONT	C	16	419.95	..	AM, FM	RC3	MA	26		I	...	PM 12
Starrett Television Corp., 601 W. 26th St., New York 1, N. Y.	ROBERT FULTON	TA	12LP4A	159.95	N	L	17	2	26.1 I	3	PM 5
	WILLIAM PENN	TA	12LP4A	179.95	N	MA	17	2	26.1 I	3	PM 5
	ROGER WILLIAMS	TA	16RP4A	199.95	N	L	17	2	26.1 I	3	PM 5
	JAMES BUCHANAN	TA	16RP4A	219.95	N	MA	17	2	26.1 I	3	PM 5
	DEWITT CLINTON	TA	16RP4A	229.95	N	BL	17	2	26.1 I	3	PM 5
	PATRICK HENRY	C	16DP4A	269.95	N	MA	17	2	26.1 I	3	PM 8
	DANIEL WEBSTER	C	16DP4A	279.95	N	BL	17	2	26.1 I	3	PM 8
	PETER COOPER	C	16DP4A	329.95	N	AM	RC3	MA	22	2	26.1 I	3	PM 8
	WASHINGTON IRVING	C	17AP4	349.95	N	MA	17	2	26.1 I	3	PM 8
	ELI WHITNEY	C	17AP4	349.95	N	BL	17	2	26.1 I	3	PM 8
	PETER STUYVESANT	C	19AP4	399.95	N	MA	18	2	26.1 I	3	PM 8
	JAMES MADISON	C	19AP4	399.95	N	MA	18	2	26.1 I	3	PM 8
	SAMUEL B. MORSE	C	19AP4	429.95	N	BL	18	2	26.1 I	3	PM 8
	JOHN MARSHALL	C	19AP4	499.95	N	AM, FM	RC3	WA	25	2	26.1 I	3	EM 8
	JOHN MARSHALL	C	19AP4	525.00	N	AM, FM	RC3	MA	25	2	26.1 I	3	PM 8
	ALEX HAMILTON	C	19AP4	550.00	N	AM, FM	RC3	BL	25	2	26.1 I	3	PM 8
Stewart-Warner Corp., 1826 D. versey Parkway, Chicago 14, Ill.	9203-A	..	14CP4	225.00	T	MA	9200-A	17	2	21.25 I	1	PM 6
	9120-A	..	16RP4	269.95	T	MA	9120-A	23	3	21.25 I	2.5	PM 6
	9120-B	..	16RP4	325.00	T	MA	9121-B	23	3	21.25 I	2.5	PM 6x9
	9120-F	..	16RP4	345.00	T	BL	9121-F	23	3	21.25 I	2.5	PM 6x9
	9120-E	..	16RP4	349.95	T	MA	9120-D	23	3	21.25 I	2.5	PM 6x9
	9120-C	..	16RP4	369.95	T	BL	9120-E	23	3	21.25 I	2.5	PM 6x9
	9121-A	..	16RP4	449.95	T	AM, FM	RC3	MA	9120-C	23	3	21.25 I	2.5	PM 6x9
	9121-B	..	16RP4	525.00	T	AM, FM	RC3	MA	9121-B	28	3	21.25 I	2.5	PM 6x9
	9122-A	..	16RP4	550.00	T	AM, FM	RC3	MA	9122-A	28	3	21.25 I	2.5	PM 12
Stolle Eng. & Mfg. Co., 3970 S. Grand Ave., Los Angeles 37, Calif.	SEMCO	C	16LP4	281.12	N	WA, BL, MA	1652	19	3	21.25 I	7.5	PM 12
	SEMCO	C	19AP4	195.00	N	WA, BL, MA	1968	19	3	21.25 I	7.5	PM 12
Stromberg-Carlson Co., 100 Carlson Rd., Rochester 3, N. Y.	MERCURY	TA	16RP4	269.95	N	MA	116	23	3	21.9 I	3	PM 5.5
	TREASURE CHEST	TA	16RP4	289.95	N	MA	116	23	3	21.9 I	3	PM 5.5
	PROVINCIAL	C	16GP4	339.95	N	MA	116	23	3	21.9 I	3	PM 12
	CHIPPENDALE	C	16GP4	395.00	N	MA	116	23	3	21.9 I	3	PM 12
	KENWOOD	C	17AP4	585.00	N	AM, FM	RC3	MA	117	23	3	21.9 I	3	PM 12
	EMPIRE	C	19AP4	429.95	N	MA	119	25	4	21.9 I	3	PM 12
	GEORGIAN	C	19AP4	499.95	N	MA	119	25	4	21.9 I	3	PM 12
	18TH CENTURY	C	19AP4	695.00	N	AM, FM	RC3	MA	119	25	4	21.9 I	3	PM 12
	CHINESE CLASSIC	C	19AP4	750.00	N	AM, FM	RC3	MA	119	25	4	21.9 I	3	PM 12
	TREASURE CHEST	TA	16RP4	299.95	N	BL	116	23	3	21.9 I	3	PM 5.5
	PROVINCIAL	C	16GP4	349.95	N	MP, BL	116	23	3	21.9 I	3	PM 12
	CHINESE CLASSIC	C	19AP4	775.00	N	AM, FM	RC3	BL	119	25	4	21.9 I	3	PM 12
Sylvania Electric Products, Inc., Radio & Television Div., 254 Rano S., Buffalo 7, N. Y.	4120M	TA	14CP4	209.95	T	MA	260	21	4	26.4 I	2	PM 6.5
	4130M	C	14CP4	259.95	T	MA	260	21	4	26.4 I	2	PM 8
	4130W	C	14CP4	249.95	T	WA	260	21	4	26.4 I	2	PM 8
	4130B	C	14CP4	269.95	T	BL	260	21	4	26.4 I	2	PM 8
	6110X	TA	16KP4	249.95	T	MA	261	21	4	26.4 I	2	PM 6.5
	6120M	TA	16KP4	269.95	T	MA	261	21	4	26.4 I	2	PM 6.5
	6120W	TA	16KP4	259.95	T	WA	261	21	4	26.4 I	2	PM 6.5
	6120B	TA	16KP4	279.95	T	BL	261	21	4	26.4 I	2	PM 6.5
	6130M	C	16KP4	319.95	T	MA	261	21	4	26.4 I	2	PM 10
	6130W	C	16KP4	309.95	T	WA	261	21	4	26.4 I	2	PM 10
	6130B	C	16KP4	339.95	T	BL	261	21	4	26.4 I	2	PM 10
	6140M	C	16KP4	399.95	T	MA	271	21	4	26.4 I	4	PM 12
	6140W	C	16KP4	359.95	T	WA	271	21	4	26.4 I	4	PM 12
	6160B	C	16KP4	509.95	T	AM, FM	RC3	BL	275	21	4	26.4 I	4	PM 12
	6150M	C	16KP4	479.95	T	AM, FM	RC3	MA	275	21	4	26.4 I	4	PM 12
	5130M	C	19AP4A	429.95	T	MA	290	21	4	26.4 I	4	PM 12
	5130W	C	19AP4A	409.95	T	WA	290	21	4	26.4 I	4	PM 12
	5130B	C	19AP4A	459.95	T	BL	290	21	4	26.4 I	4	PM 12
	5140M	C	19AP4A	479.95	T	MA	290	21	4	26.4 I	4	PM 12
	5140B	C	19AP4A	509.95	T	BL	290	21	4	26.4 I	4	PM 12
	5150M	C	19AP4A	675.00	T	AM, FM	RC3	MA	274	21	4	26.4 I	4	PM 12
	1110X	TA	16AP4A	219.95	MA	329	20	4	26.4 I	2	PM 5.5
Tech-Master Products Co., 443-5 Broadway, New York 13, N. Y.	1631	CH	16AP4	1631	27	4	21.25 S	3.5	PM 12
	1931	CH	19AP4	1931	27	3	21.25 S	3.5	PM 12
	1230	CH	12LP4	1230	26	3	21.25 S	3.5	PM 5x7
	930	CH	10BP4	930	26	3	21.25 S	3.5	PM 5x7
	UNIVERSAL	K	10 to 16"	5021	19	2	21.25 I	2.5	PM 4x6
	BLUE-RIBBON	K	10 to 12"	1223	21	2	21.25 S	3.5	PM 12
Tele-King Corp., 601 W. 26th St., New York, N. Y.	919 C	C	19BP4	T	AM, FM	RC3	MA	19	1	26.1 I	2.2	PM 12
	117 CA	TA	16RP4	T	AM	RC3	MA	18	1	26.1 I	2.2	PM 4x6
	716	C	16DP4	T	MA	19	1	26.1 I	2.2	PM 10
	312	TA	12LP4	T	MA	18	1	26.1 I	2.2	PM 4x6
	416 CAF	C	16"	T	AM, FM	RC3	MA
	114	TA	14"
	516	TA	16"
	116	C	16" Rect.
	116LO	C	16"	LO
	916CAF	C	16"	AM, FM	RC3
	201	TA	20"
	202C	C	20"
	919C	C	19"
Telequip Radio Co., 2559 W. 21st St., Chicago 8, Ill.	TD 414	TA	14BP4	169.95	N	MA	14T	18	1	23 I	4	PM 5
	CD 514	CT	14BP4	189.95	N	MA	14T	18	1	23 I	4	PM 5
	TD 416	TA	16TP4	199.95	N	MA	16T	18	1	23 I	4	PM 5
	CD 516	CT	16TP4	219.95	N	MA, BL	16T	18	1	23 I	4	PM 5
	CD 519	CT	19AP4A	299.95	N	MA, BL	19T	18	1	23 I	4	PM 5
	CD 619	CT	19AP4A	329.95	N	MA, BL	19T	18	1	23 I	4	PM 5
Tele-Tone Radio Corp., 540 W. 58th St., New York 19, N. Y.	TV322	TA	14CP4	149.95	N	PL	TM	15	1	25.75 I	2	PM 4
	TV323	TA	14CP4	169.95	N	PL	TM	15	1	25.75 I	2	PM 4
	TV318	TA	14CP4	179.95	N	MA	TM	15	1	25.75 I	2	PM 4
	TV324	TA	16TP4	199.95	N	MA	TP	15	2	25.75 I	2	

1950-51 Television Receiver Specifications

MANUFACTURER	Model	Type	Picture Tube	List Price (Dollars)	Built-in Aerial	Set Also Receives	Record Player	Cabinet Finish	Mfr's. Chassis No.	Total Tubes**	Total Rectifiers	IF Frequency	Audio Output (watts)	Speaker Size & Type	
Tele-Tone (Continued from page 102)															
	TV326R	C	16TP4	329.95	N	MA	TP	15	2	25.75 I	2	PM 10	
	TV327	C	17BP4	369.95	N	AM, FM	RC3	MA	TP	15	2	25.75 I	2	PM 10	
	TV329	C	19GP4	319.95	N	MA	TP	15	2	25.75 I	2	PM 10	
	TV328	C	19GP4	339.95	N	MA	TP	15	2	25.75 I	2	PM 10	
	TV338	TA	17BP4	209.95	N	MA	TP	15	2	25.75 I	2	PM 10	
	TV314	TA	14CP4	189.95	N	MA	20	1	37.3 I	2	PM 4x6	
	TV330	TA	16TP4	249.95	N	MA	20	1	37.3 I	2	PM 4x6	
	TV316B	C	16TP4	299.95	N	AM, FM	RC3	MA	20	1	37.3 I	2	PM 10	
	TV310	C	16TP4	349.95	N	AM, FM	RC3	MA	20	1	37.3 I	2	PM 10	
	TV331	C	16TP4	349.95	N	MA	20	1	37.3 I	2	PM 10	
	TV332	C	16TP4	349.95	N	MA	20	1	37.3 I	2	PM 10	
	TV333	C	16TP4	349.95	N	MA	20	1	37.3 I	2	PM 10	
	TV334	C	20AP4	599.95	N	AM, FM	RC3	MA	20	1	37.3 I	2	PM 10	
Trad Television Corp., 1001 First Ave., Asbury Park, N. J.															
	C1620	CT	16TP4	229.95	N	MA	T20	20	2	21.25 S	PM 12	
	C1920	CT	19AP4	299.95	N	MA	T20	20	2	21.25 S	PM 12	
	CD1620	C	16GP4	329.95	N	MA, BL	T20	20	2	21.25 S	PM 10	
	CD1920	C	19AP4	379.95	N	MA, BL	T20	20	2	21.25 S	PM 10	
	CP1620	CT	16GP4	379.95	N	FM	RC3	MA	T20	20	2	21.25 S	PM 10	
	CP1920	CT	19AP4	379.95	N	FM	RC3	MA	T20	20	2	21.25 S	PM 12	
	CD1630	C	16AP4	379.95	N	MA, BL	630T	29	2	21.25 S	PM 10	
	CD1930	C	19AP4	429.95	N	MA, BL	630T	29	2	21.25 S	PM 10	
	D-250	CO	19AP4	695.00	N	MA	630T	32	3	21.25 S	PM 10	
	P-13	CO	5TP4X	1695.00	N	MA	P49	36	3	21.25 S	PM 10	
	P-14	CO	5TP4X	1495.00	N	MA	P49	36	3	21.25 S	PM 8	
	COMM.-IN-CHIEF	CU	5TP4X	995.00	N	MA	P50	31	3	21.25 S	PM 12	
Trans-Vue Corp., 1139 S. Wabash, Chicago, Ill.															
	PHOENIX	TA	17BP4A	199.95	T	MA, BL	1600	19	2	25.75 I	4.5	PM 5	
	WINFIELD	CT	17BP4A	239.95	T	MA, BL	1600	19	2	25.75 I	4.5	PM 8	
	ARISTOCRAT	CT	17BP4A	269.95	T	MA, BL	1600	19	2	25.75 I	4.5	PM 8	
	MANHATTAN	C	17BP4A	279.95	T	MA, BL	1600	19	2	25.75 I	4.5	PM 8	
	ALEXANDER	C	17BP4A	299.95	T	MA, BL	1600	19	2	25.75 I	4.5	PM 8	
	DIANA	C	17BP4A	299.95	T	BL	1600	19	2	25.75 I	4.5	PM 8	
	BRISTOL	TA	17BP4A	189.95	T	MA	1600	19	2	25.75 I	4.5	PM 8	
	KENT	C	17BP4A	219.95	T	MA	1600	19	2	25.75 I	4.5	PM 8	
	BUCKINGHAM	C	17BP4A	199.95	T	MA, BL	1600	19	2	25.75 I	4.5	PM 8	
Trav-Ler Radio Corp., 571 W. Jackson Blvd., Chicago 8, Ill.															
	62R50	TA	16RP4	149.95	N	L	62R50	18	2	21.75 I	2	PM 4x6	
	63R50	TA	16RP4	179.95	N	MA	63R50	18	2	21.75 I	2	PM 4x6	
	64R50	C	16RP4	199.95	N	MA	64R50	19	2	21.75 I	2	PM 6x9	
	65G50	C	16GP4	229.95	N	MA	65G50	19	2	21.75 I	2	PM 6x9	
	16R50	C	16RP4	249.95	N	MA	16R50	22	2	21.75 I	2	PM 6x9	
	16G50	C	16GP4	249.95	N	MA	16G50	22	2	21.75 I	2	PM 6x9	
	16R80	C	16RP4	269.95	N	MA	16R80	22	2	21.75 I	2	PM 6x9	
	19A50	C	19AP4	299.95	N	MA	19A50	22	2	21.75 I	2	PM 6x9	
	16R70	C	16RP4	299.95	N	AM	RC3	MA	16R70	22	2	21.75 I	2	PM 6x9	
U. S. Television Mfg. Corp., 3 W. 61st St., New York 23, N. Y.															
	T-16030P	TA	16DP4	349.95	MA	T16030	26	4	25.75 S	5	PM 12	
	T-19031P	TA	19DP4	449.95	MA	T19031	27	4	25.75 S	5	PM 12	
	C-16030M	CT	16DP4	479.95	BL	C16030	26	4	25.75 S	5	PM 12	
	C-16030P	CT	16DP4	429.95	MA	C16030	26	4	25.75 S	5	PM 12	
	C-16030P	CT	16DP4	459.95	MA	C16030	26	4	25.75 S	5	PM 12	
	C-19031P	CT	19DP4	499.95	MA	C19031	27	4	25.75 S	5	PM 12	
	C-19031P	CT	19DP4	549.95	MA	C19031	27	4	25.75 S	5	PM 12	
	C-19031M	CT	19DP4	579.95	BL	C19031	27	4	25.75 S	5	PM 12	
	C-16024	CT	16DP4	339.95	MA	C16024	20	4	25.75 S	5	PM 12	
Video Corp. of America, 229 W. 28th St., New York 1, N. Y.															
	410-T	TA	16XP4	169.95	N	MA	410-T	15	2	45 I	3.5	PM 10	
	601-T	TA	16XP4	199.95	N	MA	601-T	15	2	45 I	3.5	PM 10	
	611-C	C	16XP4	239.95	N	MA	611-C	15	2	45 I	3.5	PM 10	
	611-CO	C	16XP4	249.95	N	BL	611-C	15	2	45 I	3.5	PM 10	
	750-CD	C	17HP4	279.95	N	MA	750-C	15	2	45 I	3.5	PM 10	
	750-CDO	C	17HP4	299.95	N	BL	750-C	15	2	45 I	3.5	PM 10	
	912-C	C	19FP4A	319.95	N	MA	912-C	15	2	45 I	3.5	PM 10	
	912-CO	C	19FP4A	339.95	N	BL	912-C	15	2	45 I	3.5	PM 10	
	922-CD	C	19FP4A	339.95	N	MA	922-C	15	2	45 I	3.5	PM 10	
	922-CDO	C	19FP4A	359.95	N	BL	922-C	15	2	45 I	3.5	PM 10	
	1625M	C	16CP4	359.95	N	AM	RC3	MA	1625M	22	3	45 I	3.5	PM 10	
Video Products Corp., 42 West St., Red Bank, N. J.															
	3019C	C	19"	349.00	PC	MA	630K-2C	26	3	26.25 S	4	PM 12
	H.D.5119	C	19"	379.00	PC	MA	630K-2C	26	3	26.25 S	4	PM 12
	TRADITIONAL	C	19"	525.00	PC	MA	630K-2C	26	3	26.25 S	4	PM 12
	MODERN	C	19"	540.00	PC	MA, BL	630K-2C	26	3	26.25 S	4	PM 12
Westinghouse Electric Corp., Sunbury, Pa.															
	H624T16	TA	16RP4	219.95	T	PL	V2172	21	2	45.75 I	2.5	PM 5	
	H626T16	TA	16RP4	249.95	T	MA	V2172	21	2	45.75 I	2.5	PM 5	
	H627K16	CT	16JP4	329.95	N	MA	V2171	21	2	45.75 I	2.5	PM 10	
	H628K16	CT	16JP4	299.95	N	MA	V2171	21	2	45.75 I	2.5	PM 10	
	H629K16	CT	16JP4	325.00	N	BL	V2171	21	2	45.75 I	2.5	PM 10	
	H630T14	TA	14BP4	199.95	T	MA	V2176	21	2	45.75 I	2.5	PM 5	
	H631K19	C	19" Rect.	399.95	N	MA	V2174	24	2	45.75 I	4	PM 12	
	H632T14	TA	14BP4	189.95	T	PL	V2176	21	2	45.75 I	2.5	PM 5	
	H633C17	C	16RP4	469.95	N	AM, FM	RC3	MA	V2173	26	2	45.75 I	4	PM 12	
	H634C17	C	16RP4	489.95	N	AM, FM	RC3	BL	V2173	26	2	45.75 I	4	PM 12	
Zenith Radio Corp., 6001 Dickens St., Chicago, 39, Ill.															
	H2227R	TA	12UP4B+	179.95	N	MA	22H20	19	3	41.25 I	2.5	PM 5,25	
	H2227E	TA	12UP4B+	189.95	N	BL	22H20	19	3	41.25 I	2.5	PM 5,25	
	H2228R	TA	12UP4B+	199.95	N	MA	22H20	19	3	41.25 I	2.5	PM 5,25	
	H2250R	C	12UP4B+	239.95	N	MA	22H20	19	3	41.25 I	2.5	PM 10	
	H2255E	C	12UP4B+	259.95	N	BL	22H20	19	3	41.25 I	2.5	PM 10	
	H2329R	TA	16TP4B	239.95	N	MA	23H22Z	20	3	41.25 I	2.5	PM 5,25	
	H2328R	TA	16TP4B	249.95	N	MA	23H22Z	20	3	41.25 I	2.5	PM 5,25	
	H2328E	TA	16TP4B	259.95	N	BL	23H22Z	20	3	41.25 I	2.5	PM 5,25	
	H2352R	C	16TP4B	299.95	N	MA	23H22Z	20	3	41.25 I	2.5	PM 10	
	H2353E	C	16TP4B	309.95	N	BL	23H22Z	20	3	41.25 I	2.5	PM 10	
	H2438R	C	16GP4B+	299.95	N	MA	24H20	21	3	41.25 I	2.5	PM 10	
	H2449E	C	16GP4B+												