

## - TELEVISION RECEIVER SPECIFICATIONS -

COMPILED FROM DATA SUPPLIED BY MANUFACTURERS

Trade Name	ANDREA		ATC				Du MONT				GAROD		G. E.					PILOT			RCA-VICTOR				STEWART-WARNER		WESTINGHOUSE							
Manufacturer	ANDREA RADIO CORP.		AMERICAN TELEVISION CORP.				ALLEN B. DuMONT LABS., Inc.				GAROD RADIO CORP.		GENERAL ELECTRIC CO.					PILOT RADIO CORP.			RCA MFG. CO., Inc.				STEWART-WARNER CORP.		WESTINGHOUSE ELECTRIC SUPPLY CO.							
Model No.	1F5	2F5	A35	V45	V55	VK5	180	181	182	183	101	102C	HM 171	HM 185	HM 225	HM 226	HM 275	T909	TC 909	TC 1209	TT5	TRK5	TRK9	TRK 12	-				WRT 700	WRT 701	WRT 702	WRT 703		
Cabinet	Table	Console	Table	Console	Console	Console	Table	Console				Table	Console	Table					Console	Table	Console													
Range	44-50 50-56 MC		Variable Selector				4 Television Channels				44-50 50-56 66-72 Mc		• • • • •					5 Television Channels			5 Television Channels				7 Television Bands and 5rd B.C.		5 Television Bands							
Equipped for other than RMA Standards	No		No				Yes				No		No					No			No				No		No							
Sight and Sound	Both		Both				Both				Both		No <sup>†</sup>					Both			No <sup>†</sup>				Both		No <sup>†</sup>				Both			
All-Wave Receiver	No	Yes	No	Yes	No	Yes	No	Yes	•	•	No	B.C. Band Only	No	No	No	Yes	Yes	No	B.C. Band Only	No	Yes	Yes	Yes	B.C. Band Only	No	Yes	Yes	Yes	B.C. Band Only	No	Yes	Yes	Yes	
Speaker (Inches)	6 1/2	8 & 12	•	•	•	•	•	•	•	•	6	12	-	•	•	12	12	8	12	12	-	12	12	12	12	12	12	12	12	12	12	12	12	
I-F Channels MC. Sight Sound	•	•	•	•	•	•	7.4	7.4	7.4	7.4	11.5	8.25	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	
Deflection	Electrostatic	Electrostatic				•	Electrostatic				Electrostatic	Electrostatic	Magnetic					Magnetic	Electrostatic	Magnetic	Magnetic	Electrostatic	Magnetic											
Power Supply Voltage	110-115 V. 60~		110-120 V. 60~				110-115 V. 60~				110-120 V. 60~		110-115 V. 60~					110-115 V. 60~			110-120 V. 60~				110-120 V. 60~		110-120 V. 60~							
Power Consumption (WATTS)	150		• • • • •				250				165		• • • • •					250			190	275	420	420	290	•	•	•	•					
Picture Size (Inches)	4X3	4 5/16	4 3/8 X 3 3/8		7X5	10 X 8				•	4 3/8 X 3 3/8	5 1/2 X 4 1/8	4 3/8 X 3 3/8		7 3/4 X 5 1/2	10 X 8		7 3/4 X 5 1/2		10 X 8	4 3/8 X 3 3/8		7 1/4 X 5 1/2	9 3/4 X 7 3/8	9 3/4 X 7 1/2		4 3/8 X 3 3/8	7 1/4 X 5 1/2	9 3/4 X 7 3/8	4 3/8 X 3 3/8	7 1/4 X 5 1/2	9 3/4 X 7 3/8		
Picture Color	Black & White		Black & White				Black & White				Black & White		Black and White					Black & White			Black and White				Black & White		Black and White							
Viewing	Direct	Incl.	Direct		Dir.	Direct				Direct	Direct		Indirect	Direct		Incl.	Direct		Incl.	Direct		Incl.	Indirect		Direct				Incl.					
Front Panel Controls Sight Sound	4	4	•	•	•	•	5	5	5	•	4 P.B. +4	4 P.B. +4	3 P.B. +4	3 P.B. +4	7 P.B. +4	•	•	5 P.B. +3	5 P.B. +3	5 P.B. +3	5	5	5	5	8 P.B.+3	7 P.B.+3	6	6	6	6	6			
Other Controls-Sight	6		• • • • •				7	7	7	•	6	5	5	5	•	•	8	8	8	6	6	6	6	7	•	•	•	•						
Tubes	16	22	•	•	•	•	21	21+ Rec	21	•	16	16+ Rec.	16	17	21	28	28	20	20+ B.C. SET.	20+ B.C. SET.	16	24	36	36	25	•	•	•	•					
Cathode-Ray Type (Dia. Inches)	1802-P4	1802-P1	1802-P4		•	114-9T				•	1802-P4	•	1802-P4	1804-P4	1803-P4	1804-P4	1803-P4	1804-P4	1803-P4	1804-P4	1803-P4	1804-P4	1803-P4	1804-P4	1803-P4	1804-P4	1803-P4	1804-P4	1803-P4	1804-P4	1803-P4	1804-P4		
Overall Dimensions (Inches)	•	•	•	24 W 4 1/2 H 16 D.	24 W 4 1/2 H 14 D.	13 1/4 W 20 1/4 H 24 1/4 D.	•	•	•	•	13 1/2 W 17 1/2 H 17 1/2 D.	•	20 W 14 1/2 H 16 D.	23 W 38 H 18 D.	•	•	•	•	•	•	19 1/2 W 16 1/4 H 19 1/2 D.	20 1/2 W 23 1/2 H 16 1/2 D.	31 1/2 W 47 1/4 H 24 1/2 D.	34 1/2 W 40 1/4 H 19 1/2 D.	36 W 36 H 18 D.	•	•	•	•					
List Price (\$)	189.00	289.00	160.00	•	•	395.00	395.00	540.00	445.00	•	•	•	•	•	•	•	•	250.00	295.00	475.00	189.00	295.00	450.00	600.00	•	•	•	•						
Special Features	ALSO KIT FORM	-	-	-	-	-	-	-	-	-	-	-	•	-	-	-	-	-	-	-	•	-	-	-	-	-	-	-	-	-	-	-		

• INFORMATION NOT SUPPLIED.

† SEPARATE CATHODE-RAY TUBE CABINET.

\* TENTATIVE; MAY BE CHANGED TO 3-BAND RECEIVER.

Courtesy of Dennis Choinski